



# P.A. SYSTEM



## FEATURES:

- \* Stereo output power 2x75W/4  $\Omega$  (RMS)
- \* 4 lines input (XLR)
- \* 1 Stereo input (1/4" Phone Jack)
- \* Treble Bass reverb and level Control on each channel
- \* 60mm high quality slide fader
- \* Master Volume Control
- \* 2x5 Band Graphic equalizer (with feedback display)
- \* Built - in switch power supply
- \* Built - in electronic reverb (ZH0402E10P)
- \* Built - in DSP (ZH0402D10P)
- \* Stereo (CD / Tape) input with level control



## MIXER

- \* Power output: 2 x 75W/4  $\Omega$
- \* Frequency response: 20Hz-20KHz  $\leq$  1dB
- \* THD: 20Hz-20KHz  $\leq$  0.1%
- \* Channel EQ:
  - High 10KHz  $\pm$  15dB
  - Low 100Hz  $\pm$  15dB
- \* Power requirements:
  - 110VAC, 60Hz, 200VA
  - 230VAC, 50Hz, 200VA

บริษัทหน้าจอกด: คลินิกคอมพิวเตอร์

(ข้างศูนย์ Yamaha ศรีเทพ)

โทร.056-755-164,086-88-333-43

[www.clinic-computer.com](http://www.clinic-computer.com)

[hmomee@gmail.com](mailto:hmomee@gmail.com)

## SPEAKER

- \* 2-Way (10")
- \* Power capacity: 100W
- \* Impedance: 4  $\Omega$
- \* Frequency response: 60Hz-20KHz
- \* Sensitivity: 94dB
- \* Crossover frequency: 4KHz

## ACCESSORY

- \* MIXER x 1
- \* SPEAKERS x 2
- \* SPEAKER CABLES x 2
- \* MICROPHONE CABLE x 1
- \* MICROPHONE x 1
- \* CABINET STANDS x 2



Portable



Closed complete  
P.A. system